

LIFEGARD® Quiet One® Pumps INSTRUCTIONS

Models: 800, 1200, 2200, 3000, 4000, 5000
6000, 9000, 14000 and 16000

Quiet One® Pumps feature a patented system that provides high hydraulic performance with lower energy consumption.

IMPORTANT SAFETY INSTRUCTIONS

WARNING: To guard against injury, basic safety precautions should be observed, including the following.

READ AND FOLLOW ALL SAFETY INSTRUCTIONS

WARNING: To avoid possible electric shock, special care should be taken since water is employed in the use of aquarium equipment. For each of the following situations, do not attempt repairs by yourself. Return the appliance to an authorized service facility for service or discard the appliance.

- CAUTION:** If the appliance shows any sign of abnormal water leakage, immediately unplug it from the power source.
- Carefully examine the appliance after installation. It should not be plugged in if there is water on parts not intended to be wet.
- Do not operate any appliance if it has a damaged cord or plug, or if it doesn't work properly or has been dropped or damaged in any manner.
- To avoid the possibility of the appliance plug or receptacle getting wet, position the aquarium stand, tank or the fountain to one side of a wall-mounted receptacle to prevent water from dripping onto the receptacle or plug. A "drip-loop" (fig. 1) should be arranged by the user for each cord connecting an aquarium appliance to a receptacle. The "drip-loop" is the part of the cord below the level of the receptacle or the connector if an extension cord is used, which prevents water travelling along the cord and coming in contact with the receptacle. If the plug or socket does get wet, DON'T unplug the cord. Disconnect the fuse or circuit breaker that supplies power to appliance. Then unplug and examine for presence of water in the receptacle.
- Close supervision is necessary when any appliance is used by near children.
- To avoid injury, do not contact moving parts or hot parts such as heaters, reflectors, lamp bulbs and similar.
- Always unplug the appliance from the outlet when not in use, before putting on or taking off parts and before cleaning. Never yank cord to pull plug from outlet. Grasp the plug and pull to disconnect.
- Do not use the appliance for other than intended use. The use of attachments, not recommended or sold by the manufacturer of the appliance, may cause an unsafe condition.
- Do not install or store the appliance where it will be exposed to the weather or to temperatures below freezing.
- Make sure the appliance is installed and mounted securely before operating it.
- Read and observe all the important notices regarding the installation and operation procedures.

- If an extension cord is necessary, a cord with a proper rating should be used. A cord rated for less amperes or watts than the appliance rating may over heat and cause a safety hazard. Care should be taken to arrange the cord so that it will not be tripped over or pulled.
- This appliance has a polarized plug (one blade is wider than other). As a safety feature, this plug will fit in a polarized outlet only one way. If the plug does not fit fully in the outlet, reverse the plug. If it still does not fit, contact a qualified electrician. Never use with an extension cord unless the plug can be fully inserted. Do no attempt to circumvent this safety feature.

CAUTION: Appliance must be connected to a circuit that is protected by a Ground Fault Circuit Interrupter.

WARNING: To reduce the risk of electric shock, use only on portable self-contained fountains no larger than 5 feet in any dimension.

SAVE THESE INSTRUCTIONS



ETL us CE
Intertek

INSTALLATION:


Models: 800, 1200, 2200, 3000, 4000, 5000 & 6000 (see "Pond section")

AQUARIUMS / FOUNTAINS:

Position the aquarium and stand to one side of a wall mounted receptacle to avoid the possibility of water dripping onto the receptacle or plug. Install a "drip loop" with the cord.


Model 800

The water flow rate is adjustable by means of the Flow Control Dial A (Fig.2). The pump can be connected with 1/2" fittings and accessories.





Model 1200 version with submersible front housing

The pump can be connected with 1/2" fittings and accessories on the output side. The front housing with Flow Control Dial A (Fig.3) is used in submersible applications and allows for variation of the flow rate and head of the pump.




Models 1200-2200-3000-4000-5000-6000 version with long pre-chamber.

Model 1200 = 1/2", Models 3000-4000-5000-6000 = 1". The threads are standard MPT and can be used with a vast range of fittings and accessories. (Fig.4 and 5)



POONDS:

Slide the strainer onto the pre-chamber, then place the sponge in position on strainer. Choose desired spray attachment and position on telescopic tube. Screw telescopic tube onto pump. Place pump in pond on a flat surface away from over populated plant area. Regulate the tube's height so the jet spray is always over the water surface. Unwind electric cable and place in area where it cannot be damaged. When pump is functioning, you can regulate the dimensions of spray using the diverter valve on the telescopic tube.



INSTALLATION:

Models: 9000, 14000, & 16000



Position the pump, taking care that the cable is in an area where it cannot be damaged. The pump may be secured with screws through the special brackets situated on the bottom of the pump itself. The pump is threaded both on suction and output, with a 1 1/2" thread. The thread is a standard MPT and allows use of a vast range of standard fittings and accessories.

POND Models 9000-14000-16000

Filter Basket

Fit the filter basket supplied (Fig.7) following the sequence indicated:

- Screw the coupling A (1 1/2") to the output of the pump, then screw the hose adapter B (1 1/2") onto the coupling.
- Screw the nut D (1 1/2") and the hose adapter (1 1/2") through the hole in the prefilter basket C and then close the 2 sections of the prefilter basket (C & F) using the special hooks G provided (8 pcs).
- Connect the flexible hose H (1 1/2") to the hose adapter on the pump and on the prefilter basket.



Water plays

Install the water play as in the drawing (Fig.8) • Fix the diverter "T"-valve flow adjuster I (1 1/2") to the delivery of the pump, then screw on in succession the sleeve L (from 1 1/2" to 1"), the pipe M (1"), the sleeve N (1"), the second pipe M (1"), the second sleeve N and finally the jet nozzle P.

POND MODEL 14000 REMOTE

Receiving antenna

Install the external receiving antenna of the pump as follows: • Insert the antenna cable in the telescopic antenna holding tube provided, as indicated in (Fig.9.) • Insert the antenna holding tube in the special support in the rear part of the pump, (Fig.10)

IMPORTANT

The antenna cable must extend at least 8" (20 cm) above the level of the water by regulating the height of the telescopic antenna holding tube.

R.F. transmitter

In the POND-REMOTE version the pump functions are managed at a distance by the R.F. transmitter (Fig.11). Once pump installation has been completed, insert the battery in the R.F. transmitter (12V).

Key Symbol Function

- 1 + 4 ON/OFF (press at the same time to turn pump ON or OFF)
- 1 + + Speed (increase speed and flow rate)
- 4 - - Speed (decrease speed and flow rate)
- 2WP Water Play
- 3 TIMER Timer

Starting / stopping the pump.

- ◆ The pump is started by pressing the keys "1" and "4" simultaneously for about 2 seconds.
- ◆ The pump is stopped by repeating the operation described above.

Increasing / decreasing the speed and flow rate.

- ◆ When the button "1" is pressed the pump increases the speed and flow rate.
- ◆ When the button "4" is pressed the pump decreases the speed and flow rate.

Water Play Features

- ◆ When the button "WP" is pressed only once, Water Play Feature No. 1 starts. The jet of water grows to its maximum height, remains in position for about 2 seconds, and then falls to the minimum value and remains there for about 2 seconds. The sequence is repeated cyclically until it is changed.
- ◆ When the button "WP" is pressed a second time, Water Play Feature No. 2 starts. The jet of water grows to its maximum height, stops for a few instants, falls rapidly to about 1/4, rises to about 3/4 and pauses for a few instants, falls again rapidly to about 1/4 and returns to maximum height. The sequence is repeated cyclically until it is changed.
- ◆ When the button "WP" is pressed a third time, Water Play Feature No. 3 starts. The jet of water rises to about 1/4 of its height, falls to minimum, rises again to about 1/2, falls again to about 1/4, rises to about 3/4, falls again to 1/2, returns to maximum level then falls to "zero" level. The sequence is repeated cyclically until it is changed.

Note: The passage to the various water plays is sequential and progressive. Whenever the "WP" key is pressed you move on to the next play, WP1-WP2-WP3-WP1-WP2, etc. e.g. To pass from WP3 to WP2 you must pass through WP1 and not the reverse.

Timer

The time management system is represented in 8 hour fixed modules that are already programmed as follows:

- The pump is supplied already programmed in "ON" function (at 50% of its power). When it is connected to the electric outlet, the pump starts automatically in the condition described.
- When the button "3" is pressed only once (for about 2 seconds), the pump works for 8 hours in "ON" and 16 hours in "OFF".
- When the button "3" is pressed a second time (for about 2 seconds), the pump works for 16 hours in "ON" and 8 hours in "OFF".
- When the button is pressed again, the pump returns to the initial "ON" function. **Note:** In the event of a black-out or disconnection from the power outlet, the pump always starts again in the "ON" position described in point "a".

To start the pump you must always repeat the programming of the desired functions.

IMPORTANT!!!!

- ◆ The indication that the signal has been transmitted to the pump is visibly shown by the jet of water which falls to minimum level for a few seconds.
- ◆ To change the set program it is necessary to turn the pump "OFF" and then input the desired program.
- ◆ **FOR SAFETY REASONS IF THE MOTOR IS BLOCKED, THE PUMP IS PROGRAMMED TO MAKE UP TO 20 ATTEMPTED STARTS, THEN IT STOPS. TO RESET STARTING, YOU MUST SWITCH OFF THE POWER SUPPLY TO THE PUMP AND THEN SWITCH IT ON AGAIN.**

PUMP MAINTENANCE:

Trouble Shooting

If pump should stop working first check for the following:

- 1. SHAFT BREAKAGE:** Open the pump and check if shaft is damaged or broken. Replace "ceramic shaft" if needed.
- 2. DIRTY ROTOR:** Sand, calcium or debris can cause stoppage. Open the pump and check for fragments of sand or debris. If so, disassemble rotor and rinse with fresh water. If a white film of calcium remains, rinse with vinegar, lemon or any liquid suitable for removing calcium from solid surfaces that is also non toxic to fish and plants.
- 3. NOISY PUMP:** Open the pump and check if debris has clogged the rotor. If no obstructions are causing the noise, replace the impeller assembly and shaft.



Fig. 9



Fig. 10




Fig. 11

SERVICING: Quiet One® 800 - 1200 series Pump

1. Completely disconnect the pump from your system and the power outlet.
2. QuietOne 800
3. QuietOne 800
4. QuietOne 800
5. QuietOne 1200
6. QuietOne 1200
7. QuietOne 1200
8. QuietOne 1200

2. Remove the gray front housing by squeezing it and pull it out from the bottom groove, then gently pull up and out to clear the securing tab on the top of the pump.
3. Pull the **impeller** straight out of the **impeller and steel shaft**.
4. Clean the pump and impeller chamber, as well as the **impeller**. Check the **steel shaft** for signs of rust or if it wiggles or comes out of the pump. Lubricate the **impeller** and **steel shaft** using silicone lubricant.
5. Re-insert the **impeller** into the **impeller chamber**, then replace the gray housing, making sure it fits into the securing tabs.

SERVICING: Quiet One® 2200 - 3000 - 4000 series Pump

1. Completely disconnect the pump from your system and the power outlet.
2. Remove the gray front housing by gently squeezing the sides and pulling out until it comes off.
3. Twist the gray **volute** counter-clockwise until it slips out of the grooves, then pull it straight out.
4. QuietOne 2200
5. QuietOne 2200
6. QuietOne 2200
7. QuietOne 2200
8. QuietOne 2200
9. QuietOne 2200
10. QuietOne 2200
11. QuietOne 2200
12. QuietOne 2200
13. QuietOne 2200
14. QuietOne 2200
15. QuietOne 2200
16. QuietOne 2200
17. QuietOne 2200
18. QuietOne 2200
19. QuietOne 2200
20. QuietOne 2200
21. QuietOne 2200
22. QuietOne 2200
23. QuietOne 2200
24. QuietOne 2200
25. QuietOne 2200
26. QuietOne 2200
27. QuietOne 2200
28. QuietOne 2200
29. QuietOne 2200
30. QuietOne 2200
31. QuietOne 2200
32. QuietOne 2200
33. QuietOne 2200
34. QuietOne 2200
35. QuietOne 2200
36. QuietOne 2200
37. QuietOne 2200
38. QuietOne 2200
39. QuietOne 2200
40. QuietOne 2200
41. QuietOne 2200
42. QuietOne 2200
43. QuietOne 2200
44. QuietOne 2200
45. QuietOne 2200
46. QuietOne 2200
47. QuietOne 2200
48. QuietOne 2200
49. QuietOne 2200
50. QuietOne 2200
51. QuietOne 2200
52. QuietOne 2200
53. QuietOne 2200
54. QuietOne 2200
55. QuietOne 2200
56. QuietOne 2200
57. QuietOne 2200
58. QuietOne 2200
59. QuietOne 2200
60. QuietOne 2200
61. QuietOne 2200
62. QuietOne 2200
63. QuietOne 2200
64. QuietOne 2200
65. QuietOne 2200
66. QuietOne 2200
67. QuietOne 2200
68. QuietOne 2200
69. QuietOne 2200
70. QuietOne 2200
71. QuietOne 2200
72. QuietOne 2200
73. QuietOne 2200
74. QuietOne 2200
75. QuietOne 2200
76. QuietOne 2200
77. QuietOne 2200
78. QuietOne 2200
79. QuietOne 2200
80. QuietOne 2200
81. QuietOne 2200
82. QuietOne 2200
83. QuietOne 2200
84. QuietOne 2200
85. QuietOne 2200
86. QuietOne 2200
87. QuietOne 2200
88. QuietOne 2200
89. QuietOne 2200
90. QuietOne 2200
91. QuietOne 2200
92. QuietOne 2200
93. QuietOne 2200
94. QuietOne 2200
95. QuietOne 2200
96. QuietOne 2200
97. QuietOne 2200
98. QuietOne 2200
99. QuietOne 2200
100. QuietOne 2200
101. QuietOne 2200
102. QuietOne 2200
103. QuietOne 2200
104. QuietOne 2200
105. QuietOne 2200
106. QuietOne 2200
107. QuietOne 2200
108. QuietOne 2200
109. QuietOne 2200
110. QuietOne 2200
111. QuietOne 2200
112. QuietOne 2200
113. QuietOne 2200
114. QuietOne 2200
115. QuietOne 2200
116. QuietOne 2200
117. QuietOne 2200
118. QuietOne 2200
119. QuietOne 2200
120. QuietOne 2200
121. QuietOne 2200
122. QuietOne 2200
123. QuietOne 2200
124. QuietOne 2200
125. QuietOne 2200
126. QuietOne 2200
127. QuietOne 2200
128. QuietOne 2200
129. QuietOne 2200
130. QuietOne 2200
131. QuietOne 2200
132. QuietOne 2200
133. QuietOne 2200
134. QuietOne 2200
135. QuietOne 2200
136. QuietOne 2200
137. QuietOne 2200
138. QuietOne 2200
139. QuietOne 2200
140. QuietOne 2200
141. QuietOne 2200
142. QuietOne 2200
143. QuietOne 2200
144. QuietOne 2200
145. QuietOne 2200
146. QuietOne 2200
147. QuietOne 2200
148. QuietOne 2200
149. QuietOne 2200
150. QuietOne 2200
151. QuietOne 2200
152. QuietOne 2200
153. QuietOne 2200
154. QuietOne 2200
155. QuietOne 2200
156. QuietOne 2200
157. QuietOne 2200
158. QuietOne 2200
159. QuietOne 2200
160. QuietOne 2200
161. QuietOne 2200
162. QuietOne 2200
163. QuietOne 2200
164. QuietOne 2200
165. QuietOne 2200
166. QuietOne 2200
167. QuietOne 2200
168. QuietOne 2200
169. QuietOne 2200
170. QuietOne 2200
171. QuietOne 2200
172. QuietOne 2200
173. QuietOne 2200
174. QuietOne 2200
175. QuietOne 2200
176. QuietOne 2200
177. QuietOne 2200
178. QuietOne 2200
179. QuietOne 2200
180. QuietOne 2200
181. QuietOne 2200
182. QuietOne 2200
183. QuietOne 2200
184. QuietOne 2200
185. QuietOne 2200
186. QuietOne 2200
187. QuietOne 2200
188. QuietOne 2200
189. QuietOne 2200
190. QuietOne 2200
191. QuietOne 2200
192. QuietOne 2200
193. QuietOne 2200
194. QuietOne 2200
195. QuietOne 2200
196. QuietOne 2200
197. QuietOne 2200
198. QuietOne 2200
199. QuietOne 2200
200. QuietOne 2200
201. QuietOne 2200
202. QuietOne 2200
203. QuietOne 2200
204. QuietOne 2200
205. QuietOne 2200
206. QuietOne 2200
207. QuietOne 2200
208. QuietOne 2200
209. QuietOne 2200
210. QuietOne 2200
211. QuietOne 2200
212. QuietOne 2200
213. QuietOne 2200
214. QuietOne 2200
215. QuietOne 2200
216. QuietOne 2200
217. QuietOne 2200
218. QuietOne 2200
219. QuietOne 2200
220. QuietOne 2200
221. QuietOne 2200
222. QuietOne 2200
223. QuietOne 2200
224. QuietOne 2200
225. QuietOne 2200
226. QuietOne 2200
227. QuietOne 2200
228. QuietOne 2200
229. QuietOne 2200
230. QuietOne 2200
231. QuietOne 2200
232. QuietOne 2200
233. QuietOne 2200
234. QuietOne 2200
235. QuietOne 2200
236. QuietOne 2200
237. QuietOne 2200
238. QuietOne 2200
239. QuietOne 2200
240. QuietOne 2200
241. QuietOne 2200
242. QuietOne 2200
243. QuietOne 2200
244. QuietOne 2200
245. QuietOne 2200
246. QuietOne 2200
247. QuietOne 2200
248. QuietOne 2200
249. QuietOne 2200
250. QuietOne 2200
251. QuietOne 2200
252. QuietOne 2200
253. QuietOne 2200
254. QuietOne 2200
255. QuietOne 2200
256. QuietOne 2200
257. QuietOne 2200
258. QuietOne 2200
259. QuietOne 2200
260. QuietOne 2200
261. QuietOne 2200
262. QuietOne 2200
263. QuietOne 2200
264. QuietOne 2200
265. QuietOne 2200
266. QuietOne 2200
267. QuietOne 2200
268. QuietOne 2200
269. QuietOne 2200
270. QuietOne 2200
271. QuietOne 2200
272. QuietOne 2200
273. QuietOne 2200
274. QuietOne 2200
275. QuietOne 2200
276. QuietOne 2200
277. QuietOne 2200
278. QuietOne 2200
279. QuietOne 2200
280. QuietOne 2200
281. QuietOne 2200
282. QuietOne 2200
283. QuietOne 2200
284. QuietOne 2200
285. QuietOne 2200
286. QuietOne 2200
287. QuietOne 2200
288. QuietOne 2200
289. QuietOne 2200
290. QuietOne 2200
291. QuietOne 2200
292. QuietOne 2200
293. QuietOne 2200
294. QuietOne 2200
295. QuietOne 2200
296. QuietOne 2200
297. QuietOne 2200
298. QuietOne 2200
299. QuietOne 2200
300. QuietOne 2200
301. QuietOne 2200
302. QuietOne 2200
303. QuietOne 2200
304. QuietOne 2200
305. QuietOne 2200
- 306